

Product Name :
Astra Scientific Plunger Pump Demonstration Unit

Product Code :
Fluid Mechanics Lab0031



Description :

Astra Scientific Plunger Pump Demonstration Unit

Technical Specification :

DESCRIPTION:

The designed motor-driven plunger pump, mounted on a stainless steel plinth with a water reservoir, pulsation damper and pipework for continuous circulation. The pump head, measuring tank, pulsation damper and the water reservoir are manufactured from clear acrylic for maximum visibility. The pump outlet is connected to both a sprung loading valve and a needle valve to investigate different loading characteristics. A pressure relief valve protects the operator and the equipment. An additional valve can be used to isolate or include the pulsation damper, allowing the effect of damping to be investigated

Electronic sensors measure the instantaneous cylinder pressure within the pump, the pump displacement and the cumulative flow over a period of time.

FEATURES:

- A small-scale plunger pump demonstration unit, comprising of a water reservoir, pump, control valve, relief valve and interconnecting pipework, all mounted on a stainless steel base
- Includes both a sprung loading valve and a needle valve for loading the pump
- Equipped with electronic measurement sensors for cylinder pressure, plunger position, pump outlet pressure and cumulative flow
- Pulsation damping facility
- Transparent pump head for visibility
- Supplied with software providing full instructions for setting up, operating, calibrating and performing the teaching exercises. Facilities for logging, processing and displaying data graphically.

SPECIFICATION:

- Max flow rate: 0.725 l/m typical
- Max head: 4 bars
- Swept volume: 15mm stroke x 32mm diameter
- Pumping speed: Variable up to 60 strokes/min
- Motor power rating: 250W
- Power required: 230v, 1ph



Astra Scientific

www.astrascientific.com, **Email:** info@astrascientific.com

Address: K-88, 20th Street, Annanagar, Chennai, India – 600040 **Phone:** +91-8860605265